





Nickel Plated Brass Adaptors



Male x Female Adaptors



| Code | A | A1 | B | L | CH |
|----------|------|------|------|------|----|
| RL10/10K | 1/8" | 1/8" | 7.5 | 20 | 14 |
| RL10/13K | 1/8" | 1/4" | 7.5 | 22 | 17 |
| RL10/17K | 1/8" | 3/8" | 7.5 | 23 | 22 |
| RL13/13K | 1/4" | 1/4" | 11 | 26 | 17 |
| RL13/17K | 1/4" | 3/8" | 11 | 27 | 22 |
| RL13/21K | 1/4" | 1/2" | 11 | 30 | 26 |
| RL17/17K | 3/8" | 3/8" | 11.5 | 27.5 | 22 |
| RL17/21K | 3/8" | 1/2" | 11.5 | 30.5 | 26 |
| RL17/26K | 3/8" | 3/4" | 11 | 28 | 32 |
| RL21/21K | 1/2" | 1/2" | 14 | 33 | 26 |
| RL21/26K | 1/2" | 3/4" | 14 | 36 | 32 |
| RL21/33K | 1/2" | 1" | 13 | 30 | 38 |
| RL26/26K | 3/4" | 3/4" | 15.5 | 32.5 | 30 |
| RL26/33K | 3/4" | 1" | 12.5 | 30.5 | 38 |
| RL33/33K | 1" | 1" | 15.5 | 32.5 | 38 |




| Code | A | A1 | B | L | CH |
|---------|------|------|------|------|----|
| RL05/05 | M5 | M5 | - | - | - |
| RL05/10 | M5 | 1/8" | 4 | 14.5 | 14 |
| RL10/10 | 1/8" | 1/8" | 6 | 17 | 14 |
| RL10/13 | 1/8" | 1/4" | 6 | 20.5 | 17 |
| RL10/17 | 1/8" | 3/8" | 6 | 21.5 | 22 |
| RL13/13 | 1/4" | 1/4" | 8 | 22.5 | 17 |
| RL13/17 | 1/4" | 3/8" | 8 | 23.5 | 22 |
| RL13/21 | 1/4" | 1/2" | 8 | 26.5 | 26 |
| RL17/17 | 3/8" | 3/8" | 9 | 24.5 | 22 |
| RL17/21 | 3/8" | 1/2" | 9 | 27.5 | 26 |
| RL17/26 | 3/8" | 3/4" | 9 | 25.5 | 30 |
| RL21/21 | 1/2" | 1/2" | 10 | 28.5 | 26 |
| RL21/26 | 1/2" | 3/4" | 10 | 27 | 30 |
| RL21/33 | 1/2" | 1" | 11 | 28.5 | 38 |
| RL26/26 | 3/4" | 3/4" | 11.5 | 28 | 32 |
| RL26/33 | 3/4" | 1" | 11 | 28 | 38 |
| RL33/33 | 1" | 1" | 13 | 31 | 38 |

Nickel Plated Brass Adaptors





Male x Female Adaptors





| Code | A | A1 | L | B | CH |
|----------|------|------|----|----|----|
| RL10/10X | 1/8" | 1/8" | 22 | 6 | 14 |
| RL10/10Y | 1/8" | 1/8" | 42 | 6 | 14 |
| RL13/13X | 1/4" | 1/4" | 28 | 8 | 17 |
| RL13/13Y | 1/4" | 1/4" | 51 | 8 | 17 |
| RL17/17X | 3/8" | 3/8" | 32 | 9 | 22 |
| RL21/21X | 1/2" | 1/2" | 35 | 10 | 26 |
| RL26/26X | 3/4" | 3/4" | 50 | 12 | 30 |
| RL33/33X | 1" | 1" | 50 | 13 | 38 |

Swivel Connectors - Equal





| Code | A | B | CH1 | CH2 | L |
|---------|------|------|-----|-----|------|
| 2110-18 | 1/8" | 7.5 | 13 | 13 | 25 |
| 2110-14 | 1/4" | 11 | 16 | 15 | 33 |
| 2110-38 | 3/8" | 11.5 | 20 | 17 | 35.5 |



| Code | A | B | CH1 | CH2 | L |
|---------|------|---|-----|-----|------|
| 2115-18 | 1/8" | 6 | 13 | 13 | 24.5 |
| 2115-14 | 1/4" | 8 | 16 | 16 | 31 |
| 2115-38 | 3/8" | 9 | 20 | 18 | 34.5 |

Swivel Adaptors




| Code | Thread G | Thread R | A | A1 | A2 | NV | NV1 |
|------|----------|----------|------|----|----|----|-----|
| SF10 | 1/8" | 1/8" | 27.7 | 10 | 7 | 14 | 14 |
| SF13 | 1/4" | 1/4" | 31 | 11 | 8 | 14 | 17 |
| SF17 | 3/8" | 3/8" | 36.5 | 13 | 10 | 17 | 21 |
| SF21 | 1/2" | 1/2" | 42.5 | 16 | 12 | 22 | 26 |


Nickel Plated Brass Adaptors



Blanking Plugs



| Code | A | B | L | CH |
|------|------|-----|------|----|
| VZ05 | M5 | 4.5 | 8 | 8 |
| VZ10 | 1/8" | 6.5 | 10 | 14 |
| VZ13 | 1/4" | 9 | 13 | 17 |
| VZ17 | 3/8" | 9.5 | 13.5 | 19 |
| VZ21 | 1/2" | 10 | 14.5 | 24 |
| VZ26 | 3/4" | 11 | 16 | 30 |
| VZ33 | 1" | 12 | 17 | 40 |



| Code | A | B | L | D | CH |
|-------|------|----|------|----|----|
| ZV-13 | 1/8" | 6 | 8.5 | 14 | 5 |
| ZV-17 | 1/4" | 8 | 11 | 17 | 6 |
| ZV-17 | 3/8" | 9 | 12.5 | 20 | 8 |
| ZV-21 | 1/2" | 10 | 13.5 | 25 | 10 |

